

VGA TO BNC CONVERTER



FRONT PANEL



BACK PANEL

- **VGA Loop-Thru**
- **1024 x 768 Maximum Resolution**
- **Show your DVR screen on TV**

AP VC01-1 VGA to BNC (NTSC/PAL/SECAM) signal Converter. VGA Loop-Thru / DC 5V / Power Supply Included

This VGA to BNC converter also features a VGA output port that allows for VGA Loop-Through. You can simultaneously view video on a VGA monitor while viewing the video on your CRT, TV monitor. It converts your VGA signal to be viewing device that uses standard BNC (RCA) connector with this simple external device.

- Use TV as PC monitors to view presentations, games, pictures and movies or browse the web.
- Connects your DVR with VGA output port to existing TV or CRT monitor.
- Ideal for notebook computer users to easily connect and use a large-format monitor.
- Video standards : NTSC / NTSC-EIAJ / PAL /PAL-M / PAL-N / SECAM
- Resolutions support : 640 x 480 (up to 85Hz) / 800 x 600 (up to 85Hz) / 1024 x 768 (up to 75Hz)
- Input port : VGA (DB15)
- Dual output ports : composite video (BNC connector), VGA (DB15)
- Image controls: Horizontal and vertical size, brightness, contrast, hue, saturation, sharpness and on screen display background
- Simple and quick to install ; Windows and Mac compatible.
- No driver or operating system requirements; compatible with Windows and Mac computers

| Screen Resolution | Screen Refresh Rate |
|-------------------|----------------------|
| 640 x 480 | 60 / 72 / 75 / 85 Hz |
| 800 x 600 | 60 / 72 / 75 / 85 Hz |
| 1024 x 768 | 60 / 72 / 75 Hz |

| AP VC01-1 | |
|-------------------|---|
| Input Signal | VGA x 1 |
| Output Signal | Composite Video (BNC) x 1 / VGA x 1 (15 pin D female connector) |
| Power Consumption | 500mA |
| Power Supply | DC 5V / 1 Amp Regulated Power Supply |
| Temperature | Operation: 0 ~ 50°C / Storage: -20 ~ 85°C / Humidity: up to 95% |
| Dimensions | 125(W)mm x 96(H)mm x 30(D)mm |
| Weight | 280g |

CONNECTION DIAGRAM

